

DATE	PROJECT	FIRM	TYPE
------	---------	------	------

THE L35 INCLUDES A PATENTED OPTICAL DESIGN THAT DELIVERS A 120° BEAM ANGLE OPTION IN AN ULTRASLIM FORM FACTOR FOR PRECISE COVE LIGHTING APPLICATIONS. EXCLUSIVE FLIP TO FLAT™ HINGE DESIGN PROVIDES FLEXIBILITY WHEN MANAGING SMALL COVE DETAILS. TROV OFFERS SMOOTH, FLICKER FREE DIMMING DOWN TO 0%.



**FEATURES :**

- DIM TO 0%, ELV REVERSE PHASE
- ULTRA LOW PROFILE
- MULTI-VOLT
- FLIP TO FLAT™
- 7 CCT OPTIONS
- 80+ AND 90+ CRI OPTIONS
- IP54 INTERIOR

MODEL/ SIZE	INTERIOR/ EXTERIOR	LENGTH	POWER	CCT	CRI	VOLTAGE	OPTICS
L35	I	12" 48"	02 04 06 08 10 12	<b>WHITE CCT</b> 22 25* 27 30 35 40 50	<b>MONO COLOR</b> GR**** BL AM RD***	80 90** Blank For Color	MULT (120-277V) 120

**EXAMPLE:** L35-I-48-06-30-90-MULT-120 \*2500K is not available in 10W or 12W. \*\*90 CRI not available in 2200K, 2500K or 5000K. \*\*\*Red is not available in 12W or 10W. \*\*\*\*Green is not available in 12W. See page 2 for cables and accessories.

PERFORMANCE	WATTS	OPTIC	LUMEN OUTPUT	EFFICACY
	2W	120°	127 lm/LF ( 417 lm/m )	64 lm/W
	4W	120°	327 lm/LF ( 1073 lm/m )	82 lm/W
	6W	120°	511 lm/LF ( 1676 lm/m )	85 lm/W
	8W	120°	655 lm/LF ( 2148 lm/m )	82 lm/W
	10W	120°	916 lm/LF ( 3005 lm/m )	92 lm/W
	12W	120°	1026 lm/LF ( 3386 lm/m )	85 lm/W

ALL LUMEN DATA IS FROM 4000K 80CRI FIXTURES. PLEASE SEE PHOTOMETRY SPEC SHEET FOR ADDITIONAL LUMEN DATA.

<b>COLOR RENDERING INDEX</b>	80+, 90+					
<b>COLOR CONSISTENCY</b>	2-STEP MACADAM ELLIPSE					
<b>LUMEN DEPRECIATION / RATED LIFE</b>	WATTS	L70 @ 25C	L70 @ 50C	L90 @ 25C	L90 @ 50C	*CALCULATIONS FOR LED FIXTURES ARE BASED ON MEASUREMENTS THAT COMPLY WITH IES LM-80 TESTING PROCEDURES AND IES TM-21 CALCULATOR
	2W-8W	>73,000	>60,000	>22,000	>18,000	
	10W-12W	>150,000	>70,000	>50,000	>25,000	

<b>ELECTRICAL</b>	<b>POWER CONSUMPTION</b>	2W*/LF (6.6W/M); 4W/LF (13.2W/M); 6W/LF (19.8W/M); 8W/LF (26.4W/M); 10W/LF (33W/M); 12W/FL (39.6W/M) * 3W/LF (9.9W/M) at 220V -277V												
	<b>MAX FIXTURE RUN LENGTH</b>		2W/LF		4W/LF		6W/LF		8W/LF		10W/LF		12W/LF	
		Volts	Max Run all 1'	Max Run all 4'	Max Run all 1'	Max Run all 4'	Max Run all 1'	Max Run all 4'	Max Run all 1'	Max Run all 4'	Max Run all 1'	Max Run all 4'	Max Run all 1'	Max Run all 4'
		120	214	214	186	186	152	152	114	114	91	91	76	76
		220	374	392	340	340	277	277	209	209	95	167	95	139
		277	374	494	374	428	349	349	263	263	95	190	95	175
	<b>POWER FACTOR</b>	4W, 6W, 8W, 10W, 12W >0.9, 2W<0.9												
	<b>OPERATING VOLTAGE</b>	MULTIVOLT: 110-277VAC, 50/60 Hz												
	<b>DRIVER</b>	INTEGRAL TO FIXTURE; DE-RATED POWER AND SYNCHRONOUS START-UP AT FULL BRIGHTNESS												
	<b>STARTUP TEMPERATURE</b>	-40°F TO 122°F (-40°C TO 50°C)												
	<b>OPERATING TEMPERATURE</b>	-40°F TO 122°F (-40°C TO 50°C)												
	<b>STORAGE TEMPERATURE</b>	-40°F TO 176°F (-40°C TO 80°C)												






ECOSENSE LIGHTING INC.  
837 NORTH SPRING STREET  
SUITE 103  
LOS ANGELES, CA 90012

P • 310.496.6255  
F • 310.496.6256  
T • 855.632.6736  
855.6.ECOSEN

SPECIFICATIONS SUBJECT TO CHANGE WITHOUT NOTICE. VISIT [ECOSENSELIGHTING.COM](http://ECOSENSELIGHTING.COM) FOR THE MOST CURRENT SPECIFICATIONS.  
© 2018 ECOSENSE LIGHTING INC. ALL RIGHTS RESERVED. ECOSENSE, THE ECOSENSE LOGO, RISE, TROV, SLIM COVE AND ECOSPEC ARE REGISTERED TRADEMARKS OF ECOSENSE LIGHTING INC.  
FREEDOM TO CREATE™

ECOSENSELIGHTING.COM

1/3

DATE	PROJECT	FIRM	TYPE
<b>CONTROL</b>	<b>DIMMING</b>	110-277VAC, ELV TYPE 0.07%-100%, REVERSE PHASE, TRAILING EDGE ETC control systems require 0-10V control using EcoSense LDCM. TROV will not work with ETC phase dimmers.	
<b>PHYSICAL</b>	<b>HOUSING /LENS</b>	EXTRUDED ALUMINUM; CLEAR POLYCARBONATE; STAINLESS STEEL FASTENERS; PLASTIC ENDCAPS RUBBER OVERMOLD FOR CABLE ASSEMBLY	
	<b>WEIGHT</b>	1.2LBS / 0.55KG (1FT) ; 3.95LBS / 1.8KG (4FT)	
	<b>CONNECTORS</b>	INTEGRAL MALE/ FEMALE CONNECTORS	
	<b>ENVIRONMENT</b>	INDOOR • ETL CERTIFIED FOR DRY/DAMP LOCATIONS IP54	
	<b>BEAM ANGLE</b>	COVE	
	<b>MOUNTING OPTIONS</b>	INTEGRAL MOUNTING AND ADJUSTABLE AIMING FROM 0°-180° IN 15° INCREMENTS	
<b>FIXTURE RATING &amp; CERTIFICATIONS</b>	<b>CE, ETL CERTIFIED</b> <b>RoHS COMPLIANT</b> <b>ENERGY STAR COMPLIANT</b> <b>RCM CERTIFIED</b>	    	
<b>LIMITED WARRANTY</b>	<b>5 YEARS</b>		

**WIRING OPTIONS (MVOLT): 110-277VAC**

Power Cable Assembly, TROV, Leader/Jumper, 10 foot.....	CBL-3P-L-UNV-10*
Power Cable Assembly, TROV, Leader/Jumper, 50 foot.....	CBL-3P-L-UNV-50*
Power Cable Assembly, TROV, Jumper, 5 foot.....	CBL-3P-L-UNV-05**
Power Cable Assembly, TROV, Jumper, 1 foot .....	CBL-3P-L-UNV-01**
Power Cable Assembly, TROV, Adjustable Jumper, 0" to 7" .....	CBL-3P-L-UNV-ADJ
Power Cable Assembly, TROV, Male and Female terminator caps.....	CBL-3P-L-UNV-CAPS

\*Two (2) terminators are included with the 10' and 50' power cable. One Leader need per circuit/fixture run. Cables are not plenum rated.  
\*\* If using the 5' or 1' power cable assembly as a leader to power a run one set of CBL-3P-L-UNV-CAPS will also be need per cable.

**0-10V CONTROL OPTIONS**

100-120VAC / 277VAC Linear Dimming Control Module 0-10V - Plenum Rated ..... LDCM-PL-120-277-010V-GR  
All products come standard with ELV dimming capabilities. 0-10V Control options required for operation at 0-10V.

**OPTIONAL ACCESSORIES**

**Mounting**

Mounting Track and Clips Set, 48 Inch Track, 8 Clips..... MNT-L-TRKCLIP-48 .....48" track and clips set will work with one 48" fixture or four 12" fixtures.  
Mounting Track and Clips Set, 12 Inch Track, 2 Clips.....MNT-L-TRKCLIP-12 .....12" track will not work with 48" fixtures.  
Mounting Track Clip, TROV, Set of 2..... MNT-L-CLIP .....Clips needed = 12" fixtures need 1 set of 2 and 48" fixture needs 2 sets of 2.  
90 Degree L bracket, TROV, Set of 2.....MNT-L-LBKT .....L-Brackets needed = 12" fixtures need 1 set of 2 and 48" fixture needs 1 set of 2.  
Angle Locking Clip, TROV, Pack of 10..... MNT-L-ANGLOCK .....Angle Locks needed = 12" fixtures need 1 and 48" fixtures need 2.  
Mounting, Fine Adjustment Bracket, TROV ..... MNT-L-FAB .....Fine Adjustment Brackets needed = 12" fixtures need 1 and 48" fixtures need 2.  
\*Fine Adjustment Bracket is highly recommended for Grazing Optics.  
Mounting, Fine Adjustment L-Bracket, TROV .....MNT-L-LFAB .....Fine Adjustment L-Brackets needed = 12" fixtures need 1 and 48" fixtures need 2.  
\*Fine Adjustment L-Bracket is recommended for Asymetric Optics when aiming is needed.

**Wall Mount Arm**

Wall Mount Arm, 6 inch, TROV .....	WMA-L-CA-06
Wall Mount Arm, 12 inch, TROV.....	WMA-L-CA-12
Wall Mount Arm, 18 inch, TROV.....	WMA-L-CA-18
Wall Mount Arm, 24 inch, TROV.....	WMA-L-CA-24
Wall Mount Arm End Plate Set, TROV, Includes Left and Right.....	WMA-L-END
Wall Mount Arm Joiner Plate, TROV .....	WMA-L-JNR

Wall Mount Arms needed = For individual fixture installations two arms and one end set will be needed per fixture. For continuous run installation one endset will be needed per run. Each end set contains one left and one right end plate. One joining set will be needed per joint. One arm per fixture will be need plus one extra arm to complete the run. For example: A 10ft run made with two 4ft and two 1ft fixtures will contain; 1 x WMA-L-END, 3 x WMA-L-JNR, and 5 x WMA-L-CA-12. Leader cables are not included with wall mount arms, end sets, or joiners sets.

**Snap-on Lenses**

Snap-on Lens, Frosted, 12 inch, L35.....	LENS-L35-FROST-12
Snap-on Lens, Frosted, 48 inch, L35.....	LENS-L35-FROST-48
Snap-on Lens, Clear, 12 inch, L35 .....	LENS-L35-CLEAR-12
Snap-on Lens, Clear, 48 inch, L35.....	LENS-L35-CLEAR-48

Snap-on Lenses need = One 12" lens is needed per 12" fixture and one 48" lens is needed per 48" fixture.  
Clear lenses can be used to hold colored filters to customize the output color of any TROV fixture, except the ASYM. Color filters supplied by others.

**Landscape Stake**

Landscape Stake, 6 inch, TROV, Set of 2.....	LS-L-STK-06
Landscape Stake, 12 inch, TROV, Set of 2.....	LS-L-STK-12
Landscape Stake, 18 inch, TROV, Set of 2.....	LS-L-STK-18

Landscape Stakes needed = 12" and 48" fixtures both need one set of 2.

**Masking Plates**

Masking Plate, 3 inch high, 12 inch, L50 & L35.....	MP-L50-3H-12
Masking Plate, 3 inch high, 48 inch, L50 & L35.....	MP-L50-3H-48

Masking Plates needed = One 12" lens is needed per 12" fixture and one 48" lens is needed per 48" fixture.

**Wire Box**

Conduit Connection, Wire Box, TROV, Interior Only, L35.....	CC-L-WIREBOX
---	--------------

Wire box can be used instead of a leader cable to start a run. 1/2" conduit fitting can attach directly to the box on one end and the fixture to the other.

DATE	PROJECT	FIRM	TYPE
------	---------	------	------

