

DATE	PROJECT	FIRM	TYPE
------	---------	------	------

Trov Slim L30 0-10V Dimmer Compatibility

Dimmer Manufacturer	Dimmer	120V		230V		277V	
		MAX	MIN	MAX	MIN	MAX	MIN
L30 4W							
Lutron	Diva DVTV/DVSTV	100.0%	1.2%	100.0%	2.3%	100.0%	3.4%
Eaton	DF10P-C1	100.0%	1.2%	100.0%	2.3%	100.0%	3.5%
Wattstopper	ADF120277	100.0%	1.2%	100.0%	2.3%	100.0%	3.5%
L30 8W							
Lutron	Diva DVTV/DVSTV	100.0%	1.2%	100.0%	4.5%	100.0%	6.3%
Eaton	DF10P-C1	100.0%	1.2%	100.0%	4.7%	100.0%	6.5%
Wattstopper	ADF120277	100.0%	1.2%	100.0%	4.5%	100.0%	6.3%

Minimum and Maximum percentages are calculated by measuring light output when the dimmer is set to full bright for max, and to the lowest stable output level for min. Those measurements are then divided by the light output measured when no dimmer is installed.